

4500W



SDMO Perform 5500 T 3-Phase Generator

- 4500 Rated Watts 3 phase / 2300 Rated Watts single phase via 10A SHUKO 230v socket
- 400v three phase, PLEASE NOTE THIS GENERATOR HAS A 10A SHUKO 230v socket and not the blue 16A site type connection total out put from this socket is 2300watts
- 5.6 KVA
- Heavy-duty industrial Kohler engine
- Handle grips for easy carrying
- Rigid steel tubular carry frame
- Ideal for frequent industrial or site use

The SDMO Perform 5500T 3-Phase Generator is one of the SDMO Intens (Petrol Industrial) range of generators. It is suitable for the demanding professional's, and can be used under daily conditions i.e. long periods of work , rental, aggressive environments etc. The Kohler CH395 engine has proven time and time again superior in arduous conditions.

Features Inc:

- Kohler 4 Stroke Engine
- Ideal for Industrial Use
- Low Oil Shutdown
- 3 Year Warranty
- Automatic Circuit Breaker

Brand	KOHLER SDMO
Power Details	Kohler CH395 Engine
Phase	3-Phase
Fuel Type	Petrol Unleaded
Rated Watts (W)	4500 3 phase 2300 single phase
Max Watts (W)	4500
KVA	5.65
Voltage	400V /230V
Rated Frequency (Hz)	50
Sockets	1 x 400V 16A socket - circuit breaker / 1 x 10 amp 2 pin 230v Shuko
Fuel tank Capacity	7.3 Litres
Running Time	3.5 Hrs
Dimensions (L x W x H)	810 x 555 x 590 mm
Starting Method	Recoil
Running Time	3.5 Hrs
Dimensions (L x W x H)	810 x 555 x 590 mm
Starting Method	Recoil
Noise Value - Sound Power Level dB(A)	68
Weight	77 kg
Warranty	3 Years