

6000W



SDMO HX6000 Petrol Generator



- 5200 Rated Watts
- 6.25 KVA
- Petrol unleaded
- Honda GX390 engine
- Recoil start
- Ideal for industrial and site use

The SDMO HX6000-2 is one of the SDMO INTENS (Petrol Industrial) range of generators. It is suitable for the demanding professional's, and can be used under daily conditions i.e. long periods of work , rental, aggressive environments etc. The Honda GX390 engine has proven time and time again superior in arduous conditions.

Features Inc:

- Honda 4 Stroke Engine
- Ideal for Industrial Use
- Low Oil Shutdown
- Automatic circuit breaker

Art No	3499231003992
Brand	KOHLER SDMO
Power Details	Honda GX390
Phase	Single Phase
Fuel Type	Petrol Unleaded
Rated Watts (W)	5200
Max Watts (W)	6000
KVA	6.2
Voltage	230V / 115V
Rated Frequency (Hz)	50
DC Rated Output	12V
Sockets	2 x 230V 16A, 1 x 115V 32A & 1 x 115V 16A
Fuel tank Capacity	6.5 Litres
Running Time	2.4 Hrs @ 3/4 load
Dimensions (L x W x H)	720 x 560 x 590 mm
Starting Method	Recoil
Noise Value - Sound Power Level dB(A)	68
Weight	75 kg
Warranty	3 years