

Pramac PX Series PX4000UK 230/110V Petrol Generator



DESCRIPTION

With 40 years of experience in generators & materials handling equipment, Pramac's mission for the future is to continue growth, offering leading-edge technology and evolving to more resilient, efficient, and sustainable energy solutions to support the energy transition. Pramac's vertically integrated manufacturing processes and top-quality components ensure the optimum performance across all products. Pramac PX series generators combine endurance and functionality providing the best long lasting performance for your business.

DETAILS

- Pramac PX Series PX4000UK 230/110V Petrol Generator is compact, efficient and reliable, engineered and designed for intensive use.
- Equipped with an OHV engine which provides consistent power for multiple applications.
- Produces low noise emissions which guarantee the best working conditions.
- Practical and quick user starting instructions.
- Configured with a strong and compact frame with integrated handle and wheels for easy transportation.
- To give you confidence in this product, it is guaranteed for 1 year. This excludes fair wear and tear.

Ratings definition (ISO-8528)

ESP - Emergency Standby Power: It is the maximum power available during a variable electrical power sequence, under the stated operating conditions, for which a generating set is capable of delivering in the event of a utility power outage or under test conditions for up to 200 h of operation per year with the maintenance intervals and procedures being carried out as prescribed by the manufacturers. The permissible average power output over 24 h of operation shall not exceed 70 % of the ESP.

COP - Continuous Power: It is defined as being the maximum power which a generating set is capable of delivering continuously for an unlimited number of hours, with the maintenance intervals and procedure being carried out as prescribed by the manufacturers.

SPECIFICATIONS

Dimensions (LxWxH)mm	600 x 439 x 588
Frequency	50Hz
Voltage	230/115V
Phase	1
Emergency Standby Power ESP	3.0 kVA / 2.7kW
Continuous Power COP	2.5 kVA / 2.3kW
Engine Brand	Pramac
Engine Model	SR170F
Starting System	Recoil
Fuel	Petrol
Fuel Tank Capacity	18.5 L
Runtime	14.34 Hours
Noise Level	65db(A) @7m
Dry Weight	64.5kg
Sockets	1 x 230V 16amp socket & 1 x 110V 32amp socket

